

COMMENTS / NOTES


This DAK has no cover as it would interfere with the NI-5734 case.
 The DAK is supplied with the mounting screws.

MAC-PANEL

WWW.MACPANEL.COM

DRAWN BY
 davecooper

DATE
 19/11/2012



SHEET
 1 OF 3

DESCRIPTION

DAK, Cable, X4-BNC, SMB, HDMI,
 NI 5734

DRAWING NO.

561784X-CU

REVISION

0

Pin out for 561784X		
J1	J7	WIRE
1	1	RED
2	2	BRAID
3	3	WHITE
4	4	GREEN
5	5	BRAID
6	6	WHITE
7	7	BLUE
8	8	BRAID
9	9	WHITE
10	SHIELD	MAIN CABLE SHIELD
11	10	BLACK
12	11	BRAID
13	12	WHITE
14	13	GRAY
15	14	VIOLET
16	15	RED
17	16	WHITE
18	17	YELLOW
19	18	ORANGE
20	19	PINK
1	J2	
2	J3	
3	J4	
4	J5	


COMMENTS / NOTES

○○○○○○○
MAC-PANEL

WWW.MACPANEL.COM

DRAWN BY
davecooper

DATE
19/11/2012



SHEET
2 OF 3

DESCRIPTION

DAK, Cable, X4-BNC, SMB, HDMI,
NI 5734

DRAWING NO.

561784X-CU

REVISION

0

Installation Instructions:

Install this unit before any other DAK modules are installed into the SCOUT receiver.
Mount the Modules Carrier into the SCOUT receiver using the 2 screws at the carriers top and bottom using a screwdriver.

Mount the NI-5734 into the NI FPGA card as recommended by NI assembly manual XXX

To remove do the above in reverse order.

COMMENTS / NOTES		DRAWN BY davecooper	DATE 19/11/2012	DESCRIPTION DAK, Cable, X4-BNC, SMB, HDMI, NI 5734	
	WWW.MACPANEL.COM			DRAWING NO. 561784X-CU	REVISION 0
		SHEET 3 OF 3			