



COMMENTS / NOTES

MAC-PANEL

WWW.MACPANEL.COM

DRAWN BY  
bsalvatini

DATE  
9/25/2020



DESCRIPTION

DAK,PCB,Ext,562896,68 Pin SCSI  
Male,DDC

SHEET  
1 OF 2

DRAWING NO.

562873X1

REVISION

B

RECEIVER MODULE CONNECTOR P/N: 562896	SCSI2 CONNECTOR P/N: 5210119	SIGNAL	RECEIVER MODULE CONNECTOR P/N: 562896	SCSI2 CONNECTOR P/N: 5210119	SIGNAL	RECEIVER MODULE CONNECTOR P/N: 562896	SCSI2 CONNECTOR P/N: 5210119	SIGNAL	RECEIVER MODULE CONNECTOR P/N: 562896	SCSI2 CONNECTOR P/N: 5210119	SIGNAL
A1		1 CH3_RL_115V_IN	B1		2 CH3_S2	C1		35 CH3_RH_115V_IN	D1		36 CH3_RH_IN
A2		3 CH3_RL_IN	B2		4 CH3_S1	C2		37 DIO_1_IN	D2		38 DIO_2_IN
A3		5 DIO_1_OUT	B3		6 CH43S3	C3		39 DGND	D3		40 DIO_0_IN
A4		7 DIO_2_OUT	B4		8 CH3_S4	C4		41 SYNC_A	D4		42 SYNC_D
A5		9 DIO_3_OUT	B5		10 CH2_S2	C5		43 SYNC_C	D5		44 DIO_3_IN
A6		11 CH2_RL_115V_IN	B6		12 CH2_S1	C6		45 AGND	D6		46 CH2_RL_IN
A7		13 DIO_0_OUT	B7		14 CH2_S3	C7		47 FACTORY	D7		48 SYNC_B
A8		15 CH2_RH_115V_IN	B8		16 CH2_S4	C8		49 AGND	D8		50 EXT_FLASH_WRITE_EN_L
A9		17 CH2_RH_IN	B9		18 CH1_S2	C9		51 BOOT_SELECT	D9		52 GND_EXT
A10		19 GND_EXT	B10		20 CH1_S1	C10		53 GND_EXT	D10		54 AGND
A11		21 GND_EXT	B11		22 CH1_S3	C11		55 GND_EXT	D11		56 AGND
A12		23 CH1_RL_IN	B12		24 CH1_S4	C12		57 GND_EXT	D12		58 DGND
A13		25 CH1_RL_115V_IN	B13		26 CH0_S2	C13		59 DGND	D13		60 DGND
A14		27 CH1_RH_115V_IN	B14		28 CH0_S1	C14		61 DGND	D14		62 AGND
A15		29 CH1_RH_IN	B15		30 CH0_S3	C15		63 AGND	D15		64 AGND
A16		31 GND_EXT	B16		32 CH0_S4	C16		65 AGND	D16		66 AGND
A17		33 CH0_RL_IN	B17		34 CH0_RL_115V_IN	C17		67 CH0_RH_IN	D17		68 CH0_RH_115V_IN

COMMENTS / NOTES



WWW.MACPANEL.COM

DRAWN BY  
bsalvatini

DATE  
9/25/2020



SHEET  
2 OF 2

DESCRIPTION  
DAK,PCB,Ext,562896,68 Pin SCSI  
Male,DDC

DRAWING NO. REVISION  
B