



Wiring Assembly Instructions

0883011-02 Contact, ITA, Mini-Power, 50 Amp, 8 Awg Max, Solder.



Fig. A. (Contact Sub-Assembly)

Contact Crimp Information Table							
Wire Type	Wire Awg.	Strip Length In Inches	Crimp Tool	Hex Die Set/ Positioner	Indicator	Selecto r No.	Heat-shrink Length X Dia.
Stranded	20-8*	A) 5/16"	N/A	N/A	N/A	N/A	5/8 X 1/4

*For 8 AWG wire, skip **STEP 2**

NOTE 1: Refer to **IPC/WHMA-A-620A** standard (Ch. 11.1.2) for cable lengths, measurements and tolerance.

NOTE 2: Overall length of cable should be less 3/8" to compensate for the contact attachment.

STEP 1) wire to dimensions in "Contact Crimp Information" Table using a ruler along with a wire stripper as shown in **Fig. B.**



Fig. B.

STEP 2) Tin stripped wire, (This prevents wire strands from fraying) as in **Fig. C.**



Fig. C

STEP 3) Put contact in a fixture, insert wire in contact and solder per **IPC/WHMA-A-620A** standard (Ch. 4.9.6) for Solder Connections – Cup Terminals.

NOTE: Inspect after insertion of wire into contact to make sure no strands of wire are protruding outside the Cup of the contact.

STEP 4) Remove and inspect Contact, making sure there is no spillage of solder on the outside of Contact and meets all standards set in **IPC/WHMA-A-620A** standards. **Fig. D.**



Fig. D.

STEP 5) Slide Heat-Shrink over completed Assembly for Strain Relief, **Fig. E** below,



Fig. E

NOTE: Heat-Shrink shall not cover Weep-Hole.